



Programming the Gate Controller

The only Gate Controller that will work is a:
Chamberlin/Lift Master two (2) button 972LM.

There are two buttons on the 972LM. The one which controls the gate is the one that has a raised line. The other is for your garage door.

You must have a gate controller that works. If you don't, borrow a neighbor's.

WORD OF CAUTION:
DO NOT PRESS BOTH BUTTONS OF THE GATE CONTROLLER THAT WORKS. THAT WILL ERASE THE PROGRAMMING.

Take the new controller and press both buttons. You will see a yellow light on the back of the controller blinking slowly. While continuing to hold both buttons on the new controller, press the gate button only of the controller that works and hold the two controllers back to back for a second or two. Release the buttons on both controllers. If the programming was successful the yellow light on the new controller will blink very fast when you press the gate open button.